

Stainless Steel Exit Button With LED



S840L

What is a request to exit button?

Request to exit button or also known as a push to exit buttons. These door security products connect to access control applications that release the power to the magnetic lock to automatically unlock doors and allow free exit.

How does emergency door release work?

When and how the emergency door release is activated

When an emergency door release button is pressed. The button must be physically connected to the PACS. The button can be connected in a number of ways, which will affect how the PACS will respond to the alarm. When the fire alarm system sends an alarm signal.

Specifications

Dimensions:	115x40mm
Standard Structure:	Stainless steel Panel, Steel Button
Current Rating:	3A, 36VDC Max
Output Contact:	NO/NC/COM
Mechanical Life:	1000000 tested
Operating temp:	-10°C ~ 55°C (14°F-131°F)
Operating Humidity:	0-95% (non- condensing)
Weight:	0.14kg